

Installation Note

1. Please extract the driver source code firstly. Unzip “**ubuntu5.1.tar.gz**” to a temp working folder.
2. Enter terminal mode and change to root account by this command.
(***sudo -s***)
3. Rebuild the TouchKit driver.
 - 3.1) Locate the extracted directory. And go to the subdirectory ***/touchkit/include*** then type ***make new***
 - 3.2) change the directory to ***/touchkit*** then type ***make all***
The touchKit driver will be rebuild. (**Some packages must be installed and well configured**).
 - 3.3) type ***make install*** to begin to install at the same directory ***/touchkit***
4. Edit the daemon configuration file “***/etc/tpaneld.conf***” if there is no device port you want. The configuration should contain some parameters description as below

```
MouseMode = DRAWING
DbClickSpeed = 18
DbClickArea = 30
RclickTool = 0
Sound = 0
Port = /dev/ttyS0
Port = /dev/ttyS1
Port = /dev/psaux
Port = /dev/tkpanel0
Port = /dev/tkpanel1
```

The daemon tpaneld will scan the ports list in the configuration file to check if touchscreen controller exists or not.

/dev/tkpanel0 and ***/dev/tkpanel1*** are used for USB model.

5. Reboot